

App Features

Additional features are available via the Intellink App. To access the LiveView screen, tap the Floodlight Camera icon on the App main screen.

TIP: The Pencil icon, which opens Settings menu, is at top right corner of the LiveView screen.

MOTION DETECTION ENABLE/DISABLE

Tap: LiveView screen >>> Pencil (icon) >>> "Detection Alarm Settings" >>> "Motion Detection Alarm". (Or: LiveView >>> Alarm (icon) >>> Motion Detection Alarm)

NOTE: This setting also controls whether motion detection will trigger floodlights at night.

TALK MODE

Tap: LiveView >>> Pencil (icon) >> Basic Function Settings >>> Talk Mode.
Select: "One-Way Communication" or "Two-Way Talk"

MOTION ZONE SENSITIVITY AND ON-TIMER

Tap: LiveView >>> Motion (icon) >>> Select "Low", "Middle" or "High" and timer duration.

TIP: If the Motion icon is not visible, simply flick the LiveView icon menu upwards to show more icons.

MOTION DETECTION DO-NOT-DISTURB SCHEDULE

This Schedule will block notifications on your App during the scheduled period.

* Main screen: Tap "Me" >>> Settings >>> App Notification >>> "Do-Not-Disturb Schedule" >>> "Add Schedule" >>> "Do-Not-Disturb Device" >>> Select your Floodlight Camera >>> Left arrow (top of screen) to exit >>> Set the Schedule & Repeat parameters >>> "Save".

TIP: Check "Do-Not-Disturb Schedule" option is turned on.
Add more Schedules, if needed.

SIREN ON/OFF (to scare off an intruder)

Tap: LiveView >>> Buzzer (icon) >>> Power button to toggle audio On/Off

DEVICE SHARING (multi-user access)

Sharing can be configured from the paired login account to additional login accounts.

Tap: LiveView >>> Pencil (icon) >> Share Device >>> Add Sharing >>> Enter additional account ID >>> Tap Done to save setting

RECORDING MODE

Tap: LiveView >>> Pencil (icon) >> Storage Settings >>> Recording Mode

Select: "Event Recording" or "Non-Stop"

Appendix: Camera LED Guide

NO.	LED Status	Camera Status
1	Red LED on	System starting up
2	Red LED blinks	Standby for configuration
3	Blue LED blinks	Network pairing
4	Blue LED on	Camera online

Specifications:	
Image Sensor	1/2.9" Color CMOS
Display Resolution	1080P@15fps(1920*1080)
Mini. Illumination	0 Lux (with infrared LED on)
Focal Length	2.8mm
Viewing Angle	150° D /125° H /85° V
IR LED	10pcs 850nm LED IR distance 10m
Floodlights	2pcs floodlights combination up to 2500LM
Audio	Built-in Mic & Speaker
Wireless	802.11b/g/n WiFi @ 2.4GHz only
Wireless Security	WPA/WPA2, WPA-PSK/WPA2-PSK
PIR Motion Detection	270° PIR motion detection up to 8m
Power Consumption	<30W
Storage	Micro SD Card up to 128GB
Cloud	Support cloud storage by paid subscription
Working Temperature	-20°C ~ 60°C
Installation Height	2.4 - 3m
Power	Hardwired(AC 100-240V)

